

Registering a Non-Samsung SIP phone

There are many different manufacturers of SIP phones on the US marketplace today. Each SIP phone will be different for how you will access the setup wizard or web server page used to set the necessary parameters for the SIP phone to register and work. Once you have entered the setup wizard for the particular phone, the following options should be set correctly:

(EXAMPLE)

ENTER SETUP WIZARD:

Phone Settings >

- (Set as: **Static** or DHCP IP)
- IP address: **192.168.9.196**
- Subnet: **255.255.255.0**
- Gateway: **192.168.9.1**
- User ID, User Name, Auth Name, Auth User Name, or Display Name: **3301**
- Password: **0000**

Network Service Settings > SIP Server >

- Domain: **192.168.9.200** (This is IP address of the MP in MMC 830)
- Outbound Proxy: **192.168.9.200** (This is the IP address of the MP in MMC 830)

When the SIP Phone has registered correctly, go offhook from the SIP phone and make an internal call to test for proper operation. Also, the Technician can enter MMC 842 and check. A SIP phone that is register correctly will display the following in MMC 842:

3301 [REGISTERED]
YES

3301 [IP ADDRESS]
192.168.9.190

3301 [USER ID]
3301

3301 [PASSWORD]

3301 [TONE SRC]
USE SYSTEM TONE

3301 [CALL WAIT]
DISABLE

3301 [PHONE TYPE]
NON-SAMSUNG PHONE